

# MODEL 9260

## 34Vp-p Differential / Dual Channel Signal Amplifier



- 45MHz bandwidth
- High amplitude to 34Vp-p into 50
- High output current drive to 1A
- Fast transition time of <10ns
- Low distortion
- Custom Configuration of:
  - Gain
  - Input impedance
  - Output configuration

The 9260 is a bench-top, 2U, half 19" rack size, fully metal case, dual channel DC coupled wideband amplifier designed for high frequency, high current, signal amplification. With a high bandwidth of 45MHz, 34Vp-p into 50 ohms and up to 10W output power, the 9260 is the ideal complimentary amplifier to any signal source that needs a supporting power boost for demanding applications.

### High Current High Power

With a peak output current of 1A the 9260 enables a continuous power output of up to 10W, making it ideal for various pulse applications.

### Instrument Configuration

The 9260 can be configured to be used as two, single-ended independent channels, or as a one input with two differential outputs. The 9260's standard configuration enables a maximum output voltage of 34Vp-p into 50 ohms with a gain of x10. Other custom gain, such as x15 can be ordered at the time of the purchase, enabling clients' even wider variety of choices to solve their application.

### Output Characteristics

The outputs are located on the front panel. There are two outputs, one for each channel. When the 9260 is configured as two separate amplifiers, the outputs generate amplified signals within the range of 34Vp-p into matching load impedance at approximately 45MHz bandwidth.

### Input Characteristics

The inputs to the amplifiers can be configured to match different source impedances such as 50 , 75 , or 1M . There are three inputs for each channel:

1. Main input. This input is located on the front panel and is normally used for signal inputs.
2. Auxiliary input. This input is located on the rear panel and can be used as a summing input.
3. DC Offset input. This input is also located on the rear panel and can be used for offsetting the signal level within the specified output level window.

### Auxiliaries

The 9260 has two additional inputs for each channel allowing summation of two signals and providing an external control of DC level offset. These inputs are accessible from the rear panel only.

### Target Applications

While target applications include piezo-electronics, transducer characterization, MEMS, general electronics and scientific applications, the new 9260 is an ideal solution for virtually any wide bandwidth application that requires high voltage and high current amplification.

# MODEL 9260

## 34Vp-p Differential / Dual Channel Signal Amplifier

### Specification

#### CONFIGURATION

**Channels:** 2 with single-ended outputs; 1 with differential output

#### INPUT CHARACTERISTICS

##### MAIN INPUT

**Connector:** Front panel BNCs  
**Impedance:** 50 , 75 or 1M  
**Coupling:** DC or AC  
**Damage Level:** 12Vp-p (-6V to +6V peaks)  
**Differential Mode Accuracy:** 4%

##### INPUT AUXILIARY CHARACTERISTICS

**Connector:** Rear panel BNC  
**Impedance:** 50  
**Coupling:** DC  
**Damage Level:** 12Vp-p (-6V to +6V peaks)

##### OFFSET AUXILIARY CHARACTERISTICS

**Connector:** Rear panel BNC  
**Impedance:** 10k  
**Coupling:** DC  
**Damage Level:** ±2V  
**Accuracy:** 7%

#### OUTPUT CHARACTERISTICS

##### GENERAL

**Connector:** Front panel BNC  
**Source Impedance:** 0Ω  
**Coupling:** DC or AC  
**Protection:** Short-circuit & Thermal protection  
**Gain (50 load):** x10<sup>(2)</sup>, fixed  
**Polarity:** Normal  
**Amplitude:** 34Vp-p into matching impedance  
**Max. Output Current:** 1A

##### SQUARE WAVE CHARACTERISTICS

**Transition Time:** <10ns (typ.)  
**Aberrations:** <10%

##### SINE WAVE CHARACTERISTICS

**Bandwidth (-3dB):** 45MHz (typ.)  
**Frequency Range:** DC to 45MHz  
**Harmonics Distortion (typ.):** 10Vp-p 25Vp-p  
 1MHz <-65dBc <-54dBc  
 10MHz <-50dBc <-45dBc  
 30MHz <-38dBc <-30dBc

#### GENERAL

**Voltage Range:** 85VAC to 265VAC  
**Frequency Range:** 47Hz to 63Hz  
**Power Consumption:** 25W  
**Signal Ground:** Grounded to case ground  
**Dimensions:**  
 With Feet 315 x 102 x 395 mm (WxHxD)  
 Without Feet 315 x 88 x 395 mm (WxHxD)  
**Weight:**  
 Without Package 3.5kg  
 Shipping Weight 4kg  
**Temperature:**  
 Operating 0°C to 50°C  
 Storage -40°C to 70°C  
**Humidity:** 80% RH, non condensing  
**Safety:** CE Marked, IEC61010-1  
**Calibration:** 1 year  
**Warranty (\*):** 3 years standard

#### ORDERING INFORMATION

34Vp-p Differential / Dual-Channel Signal Amplifier

**MODEL** 9260-10-50-D-S(1)

**Gain:** 10, 15 or 20, fixed<sup>(2)</sup>  
**Input Impedance:** 50 = 50Ω  
 75 = 75Ω  
 1M = 1MΩ  
**Coupling:** D = DC  
 A = AC  
**Output Configuration:** S = Two separated channels  
 D = Single channel with differential outputs<sup>(3)</sup>

- (1) Standard Configuration  
 (2) Custom gain from x10 to x20 can be ordered however, bandwidth may change.  
 (3) Selectable by switch.  
 (4) Specification is given for the standard configuration only

### 绿测科技有限公司

广州总部: 广州市番禺区陈边村金欧大道83号江潮创意园A栋208室  
 深圳分公司: 深圳市龙华区龙华街道 油松社区东环一路1号耀丰通工业园1-2栋2栋607  
 南宁分公司: 广西自由贸易试验区南宁片区五象大道401号五象航洋城1号楼3519号  
 广州分公司: 广州市南沙区凤凰大道89号中国铁建·凤凰广场B栋1201房  
 电话: 020-2204 2442  
 传真: 020-8067 2851  
 邮箱: Sales@greentest.com.cn  
 官网: www.greentest.com.cn

